



BLACKOUT *spark* SL

XLR CONDENSER MIC FOR PRO RECORDING AND STREAMING

From studio to stream.

Ready to upgrade your home studio or streaming setup to full broadcast studio level? Blackout Spark SL brings Blue's legendary studio sound to your space. With a professional XLR connection and versatile switches, Blackout Spark SL gives you that broadcast studio voice that will transform your podcasts, Twitch® game streams and YouTube videos. The large-diaphragm cardioid condenser capsule and JFET electronics deliver superb detail and rich harmonic audio for the ultimate in professional sound. Upgrade to Blackout Spark SL and hear why Blue is the #1 choice for game streamers, podcasters and musicians worldwide.

- + XLR connection integrates perfectly with USB audio interfaces and mixers
- + Custom, large-diaphragm cardioid condenser capsule for superbly detailed, focused sound
- + Blue's Class-A JFET electronics deliver rich harmonic audio
- + 100Hz low cut filter increases clarity, reducing rumble from your room or desk
- + -20dB pad keeps your stream free of distortion when things get intense

Specifications

Transducer Type	Condenser, Pressure Gradient	S/N Ratio	73 dB-A
Polar Pattern	Cardioid	Noise Level	16.4 dB
Frequency Response	20Hz – 20kHz	Dynamic Range	119.6 dB
Sensitivity	34.9 mV/Pa at 1 kHz (1 pa = 94 dB SPL)	Power Requirements	+48V DC Phantom Power
Output Impedance	50 ohm	Weight	336g
Rate Load Impedance	not less than 1k ohm	Low Cut Filter	100Hz, 12dB per octave
Maximum SPL	136 dB SPL (1k, THD 0.5%)	PAD	-20dB

Included Accessories

Wooden storage box
Custom shock mount



[bluedesigns.com](https://www.bluedesigns.com)

Visit [bluedesigns.com](https://www.bluedesigns.com) or contact orders@bluemic.com.